

## 7-Day Digital In-Wall Programmable Timer Switch



Model #: HET01

**Description:** Wiring your lights through a timer switch like the Enerlites HET01 can help save you money while adding a level of convenience and safety to your home. This Enerlites 7-day programmable timer switch has the flexibility of being able to use eighteen different programs per week. This unit works with incandescent and halogen lighting. The large LCD screen shows time, day and load status. Manual override enables load to be turned on/off. This unit also has a built-in rechargeable battery and the programming is protected during power outages.

**Features:**

- For use with incandescent and halogen lights up to 500 watts.
- 7-day programming (up to 18 on and 18 off times per week)
- Two operating modes: Manual (conventional on/off switch) Automatic
- Sleek design mounts flush with wall plate
- Programming protected during power outages
- Manual override enables load to be turned on/off
- Built-in rechargeable battery

**Specifications:**

Voltage.....	120VAC @ 60Hz
Resistive.....	15amp, 1800W
Tungsten .....	1200W
Ballast .....	1200VA
Motor .....	1/2HP

**Testing & Code Compliance**



**Wiring Diagram:**

